

ZRC-100

Advanced Z-Wave Controller

The real easy to use Z-Wave remote controller
perfect companion with gateway

- LCD display with white color back light
- Simple and comprehensive user's interface



Feature summary:

- 100% Z-Wave compliant
- Easy to configure
- Works with Z-Wave enabled devices such as:
 - Thermostat
 - Door lock (AES 128 data, encryption)
 - Window Drapes/Blinds/Shades
 - Dimmer
 - Switches
 - Most split type air conditioners (via Remotec IR extender)
- Max. 12 scenes
- Supports multi-channel devices

- Dimensions: 161(L)*52(W)*15(H)mm
- Power sources: 4*AAA batteries
- Frequency:
 - EU & UK: 868.4MHz;
 - US/Canada: 908.4MHz;
 - AU: 921.4MHz



	Supported Command Classes	Controlled	Supported
1	COMMAND_CLASS_CONFIGURATION	Yes	No
2	COMMAND_CLASS_ASSOCIATION	Yes	Yes
3	COMMAND_CLASS_MULTI_CHANNEL_ASSOCIATION	Yes	Yes
4	COMMAND_CLASS_SCENE_CONTROLLER_CONF	No	Yes
5	COMMAND_CLASS_SCENE_ACTIVATION	Yes	No
6	COMMAND_CLASS_SCENE_ACTUATOR_CONF	Yes	No
7	COMMAND_CLASS_MULTI_CHANNEL	Yes	No
8	COMMAND_CLASS_THERMOSTAT_FAN_MODE	Yes	No
9	COMMAND_CLASS_THERMOSTAT_FAN_STATE	Yes	No
10	COMMAND_CLASS_THERMOSTAT_MODE_V2	Yes	No
11	COMMAND_CLASS_THERMOSTAT_OPERATING_STATE	Yes	No
12	COMMAND_CLASS_THERMOSTAT_SETPOINT_V2	Yes	No
13	COMMAND_CLASS_SWITCH_MULTILEVEL_V3	Yes	No
14	COMMAND_CLASS_SENSOR_MULTILEVEL	Yes	No
15	COMMAND_CLASS_SENSOR_BINARY	Yes	No
16	COMMAND_CLASS_BASIC_WINDOW_COVERING	Yes	No
17	COMMAND_CLASS_GROUPING_NAME	Yes	No
18	COMMAND_CLASS_DOOR_LOCK	Yes	No
19	COMMAND_CLASS_SECURITY	Yes	Yes

Preliminary design, subject to final specification

All information are subject to final specification.

Remotec

Website: <http://www.remotec.com.hk>