

Z-URC™

Z-Wave enabled Universal Remote Control

For controlling your AV equipments and home automated devices

Hardware:

- 81 buttons (63 operation buttons at front + 18 set up buttons at back)
- 3xAAA batteries
- Dimension: 60 x 240 x 27 mm

IR URC:

- Controls 8 A/V devices (TV,DVD,STB, AUX...)
- Support Full Set-Top-Box function keys
- Best-in-class IR learning, 15KHz to 455KHz
- Up to 100 learning commands
- 100% traceable original code library


Z-Wave:

- 3 steps XpressZetup™
- 16 groups or scenes (8 + shift 8)
- Each group and scene control up to 32 devices
- Discrete on/off buttons for every group or scene
- Max. 232 devices in a home network
- Control distance: Point to point approx. 30 meters (unlimited range through mesh networking)
- Controls Z-Wave compliant switch, dimmer devices, door sensor, curtain and etc...
- Frequency:
EU & UK: 868.4MHz
US/Canada: 908.4MHz
AU: 921.4MHz



Z-URC™ 550US

Z-URC™ 550EU



Hassle free XpressZetup™ for Z-Wave setup in 3 easy steps



	Supported Command Classes	Control	Support
1	COMMAND_CLASS_SIMPLE_AV_CONTROL	Yes	No
2	COMMAND_CLASS_CONFIGURATION	Yes	No
3	COMMAND_CLASS_CONFIGURATION_V2	Yes	No
4	COMMAND_CLASS_VERSION	No	Yes
5	COMMAND_CLASS_MANUFACTURER_SPECIFIC	No	Yes
6	COMMAND_CLASS_SWITCH_ALL	Yes	No
7	COMMAND_CLASS_SWITCH_MULTILEVEL	Yes	No
8	COMMAND_CLASS_BASIC	Yes	Yes
9	COMMAND_CLASS_SCENE_ACTIVATION	Yes	No
10	COMMAND_CLASS_ASSOCIATION	Yes	Yes
11	COMMAND_CLASS_SCENE_CONTROLLER_CONF	No	Yes

Ordering part number: BW8330 is Z-URC™ 550US
BW8332 is Z-URC™ 550EU

Remotec

Website: <http://www.remotec.com.hk>